

## M55 Remote Command List

Description	Command		Full RS232 Command	
	Hex	Dec	Hex	Dec
Angle	63	99	01,16,63,02,86	1,22,99,2,134
Audio	61	97	01,16,61,02,88	1,22,97,2,136
Check	A4	164	01,16,A4,02,45	1,22,164,2,69
Clear	56	86	01,16,56,02,93	1,22,86,2,147
Cursor Down	5E	94	01,16,5E,5E,02,8B	1,22,94,94,2,139
Cursor Left	60	96	01,16,60,02,89	1,22,96,2,137
Cursor Right	5F	95	01,16,5F,02,8A	1,22,95,2,138
Cursor Up	5D	93	01,16,5D,02,8C	1,22,93,2,140
Digit 0	52	82	01,16,52,02,97	1,22,82,2,151
Digit 1	49	73	01,16,49,02,A0	1,22,73,2,160
Digit 2	4A	74	01,16,4A,02,9F	1,22,74,2,159
Digit 3	4B	75	01,16,4B,02,9E	1,22,75,2,158
Digit 4	4C	76	01,16,4C,02,9D	1,22,76,2,157
Digit 5	4D	77	01,16,4D,02,9C	1,22,77,2,156
Digit 6	4E	78	01,16,4E,02,9B	1,22,78,2,155
Digit 7	4F	79	01,16,4F,02,9A	1,22,79,2,154
Digit 8	50	80	01,16,50,02,99	1,22,80,2,153
Digit 9	51	81	01,16,51,02,98	1,22,81,2,152
Dimmer	A3	163	01,16,A3,02,46	1,22,163,2,70
Display	5C	92	01,16,5C,02,8D	1,22,92,2,141
Enter	66	102	01,16,66,02,83	1,22,102,2,131
Marker	6E	110	01,16,6E,02,7B	1,22,110,2,123
Marker Search	6F	111	01,16,6F,02,7A	1,22,111,2,122
Menu	59	89	01,16,59,02,90	1,22,89,2,144
Open/Close	41	65	01,16,41,02,A8	1,22,65,2,168
Pause	43	67	01,16,43,02,A6	1,22,67,2,166
Play	42	66	01,16,42,02,A7	1,22,66,2,167
Power Off	A1	161	01,16,A1,02,48	1,22,161,2,72
Power On	A0	160	01,16,A0,02,49	1,22,160,2,73
Program	55	85	01,16,55,02,94	1,22,85,2,148
Random	5A	90	01,16,5A,02,8F	1,22,90,2,143
Repeat	57	87	01,16,57,02,92	1,22,87,2,146
Repeat A-B	58	88	01,16,58,02,91	1,22,88,2,145
Resolution	A2	162	01,16,A2,02,47	1,22,162,2,71
Resume	65	101	01,16,65,02,84	1,22,101,2,132
Return	67	103	01,16,67,02,82	1,22,103,2,130
Scan Back	48	72	01,16,48,02,A1	1,22,72,2,161
Scan Forward	47	71	01,16,47,02,A2	1,22,71,2,162
Set Up	68	104	01,16,68,02,81	1,22,104,2,129
Skip Back	46	70	01,16,46,02,A3	1,22,70,2,163
Skip Forward	45	69	01,16,45,02,A4	1,22,69,2,164
Slow Back	6A	106	01,16,6A,02,7F	1,22,106,2,127
Slow Forward	5B	91	01,16,5B,02,8E	1,22,91,2,142
Stop	44	68	01,16,44,02,A5	1,22,68,2,165
Subtitle	62	98	01,16,62,02,87	1,22,98,2,135
Title	64	100	01,16,64,02,85	1,22,100,2,133
Zoom	54	84	01,16,54,02,95	1,22,84,2,149

Note: IR commands use NEC encoding with customer code 859A (34202)